

Standby-Mercura~4~Rue~Louis~Pasteur~ZA~Les~Gailletrous~41260~LA~CHAUSSEE~SAINT~VICTOR~-~FRANCE~Tél.~+33(0)2~54~57~52~52~-~Fax~+33(0)2~54~56~80~00~-~export@standby-mercura.fr~-~www.standby-mercur

Mini VEGA blue with electronic control panel

Choose the control panel suitable for your MINI VEGA S lightbar Article number: 30240





Choose a control panel suitable for your MINI VEGA S lightbar

Advantages:

- Mini lightbar with integrated siren and loudspeaker
- Light, easy and prompt to install
- 3 different mounting types available
- High brightness LED lighting R65 approved

Product's codes:

LensPolycarbonateColour LEDsBlue, WhiteColour lensBlue

No. of LEDs 4 x 9 LED modules

1 x 3 LED rear module (versions

with siren)

2 x 3 LED modules (1 front + 1 rear) for versions without siren

Flash Patterns Mode: R65 double flash

 Voltage
 10-30V

 Length
 53 cm

 Height
 6.7 cm

 Width
 26.7 cm

Approval ECE R65 I, ECE R10

Includes Supplied with 4 m cable and 2-

button cigar lighter plug (magnetic model only)

CONTROL BY CCS CONTROL PANEL	Roof Connector	Control panel	Adhesive	Bolted
+ Control panel not included	-	not included (see table below)	30240*	30241*
	Yes	not included (see table below)	30244*	30245*

^{*}The control panel is mandatory and should be chosen from options listed in table below.

4-key CCS control panel	Code
for emergency vehicles	30248
for fire brigade	30249

CONTROL BY CONTROL PANEL WITH MICROPHONE AND PUBLIC AL	DDRESS Roof Connector	Control panel	Adhesive	Bolted
+ Control panel included	Yes	Handy Emergency	30256	30257
	Yes	Handy Fire brigade	30258	30259
	ded Yes	Handy Export	30260	30261

For more information, please consult the "documentation" tab below and find our product approvals here.